



30 W



60 W



120 W



180 W

Economic LED Transformer

Electronic Transformers for low-voltage LED application

Product Description

High frequency, compact size LED Transformer, operation with 24VDC LED Strip.

Product Features and Benefits

- Optimal performance thanks to the dedicated LED solution
- Lifetime, 20,000 hours
- Safe operation, SELV compliant, CB
- Safety protections including overload protection and short circuit protection
- Installation friendly, Class II
- CCC, CE, CB certificate

Applications

- Hotel, Partially light the space, Living rooms, Corridors
- Retail & Shopping Mall, Cabinet or shelf lighting
- Restaurant, Enhance the ambience, create the mood
- Decoration, Create space and layers, light sculpture


Quality

We ensure optimum quality regarding:

- System supplier
As manufactures of lamps and gear, Philips ensures that, from the earliest development stage, optimum LED light source and gear performance is designed
- International supplier
Philips LED transformer fully comply with SELV standards, IEC 61347-1, IEC 61347-2-13

Compliances and approvals

- Safety IEC61347-1 IEC61347-2-13
 - RFI < 30 MHz CISPR15 Ed 7.1
 - RFI > 30 MHz CISPR15 Ed 7.1
 - Harmonics EN 61000-3-2
 - Immunity EN61547
 - Vibration & bump tests IEC 60068-2-6 Fc IEC 60068-2-29 Eb
 - Approval marks SELV, CB, CE, CCC
 - Quality standard ISO9001
 - Environmental standard ISO14001
- RoHS compliance



Dimensions in mm

Type	A1	A2	B1	C1
Economic LED Transformer 30W 24VDC	150	140	40	28
Economic LED Transformer 60W 24VDC	211	200	40	32
Economic LED Transformer 120W 24VDC	280	268	40	34
Economic LED Transformer 180W 24VDC	300	288	50	35

Technical data

Type	Voltage (Volt)	Frequency (Hz)	Power factor	Max. output power (Watt)	Max. output current (Amp)	Output voltage (Volt)	Tc (°C)	Ta (°C)	Dimmable (Y/N)
Economic LED Transformer 30W 24VDC	220-240	50/60	0.90	6-30	1.25	24 VDC	90	-20...50	N
Economic LED Transformer 60W 24VDC	220-240	50/60	0.95	6-60	2.5	24 VDC	90	-20...50	N
Economic LED Transformer 120W 24VDC	220-240	50/60	0.95	36-120	5	24 VDC	90	-20...50	N
Economic LED Transformer 180W 24VDC	220-240	50/60	0.95	54-180	7.5	24 VDC	90	-20...50	N

Ordering and packing data

Transformer	12NC	Language	Carton		Pallet	
			Carton packing Qty pcs	Dimensions L x W x H cm	Cartons-per pallet pcs	Qty-per pallet pcs
Economic LED Transformer 30W 24VDC	913710033080	CN/EN	50	32.0 x 21.0 x 18.0	75	3750
Economic LED Transformer 60W 24VDC	913710033180	CN/EN	20	22.0 x 21.0 x 15.5	100	2000
Economic LED Transformer 120W 24VDC	913710033680	CN/EN	20	29.0 x 21.0 x 16.0	80	1600
Economic LED Transformer 180W 24VDC	913710033780	CN/EN	9	31.0 x 16.0 x 13.0	126	1134

PHILIPS

Inrush current

Type	Max quantity of ballasts Per MCB Type B 16A	Inrush current $\frac{1}{2}$ Value time at typical mains Impedance
Economic LED Transformer 30W 24VDC	28	8A/110us
Economic LED Transformer 60W 24VDC	28	8A/110us
Economic LED Transformer 120W 24VDC	11	35A/320us
Economic LED Transformer 180W 24VDC	3	60A/550us

Conversion table for max. quantities of ballasts on other types of Miniature Circuit Breaker

MCB type	Rating	Relative number of ballasts
B	16 A	100% (see table above)
B	10 A	63%
C	16 A	170%
C	10 A	104%
L, I	10 A	65%
G, U, II	16 A	212%
G, U, II	10 A	127%
K, III	16 A	254%
K, III	10 A	154%

Wiring Diagram:

30W & 60W



120W



180W




Technical data for installation

Mains operation

Rated mains voltage	220-240V
Lifetime	20,000 hours
Over voltage	Up to 290V (48 hours)
Tamb	-20°C - +50°C
Max Tcase	90°C

Protection

Short circuit protection	Yes
Overload protection	Yes
Overheating protection	Yes



Wire cross-section:

Input side	0.5 ... 0.75 mm ²
Output side	0.5 ... 0.75 mm ²

Wire stripping length:

Input side	6 ... 7 mm
Output side	6 ... 7 mm

Cable diameter:

Input side	1.7 ... 3 mm
Output side	1.7 ... 3 mm

Minimum installation distance:

between transformer	50 mm
---------------------	-------



© 2016 Philips Lighting
All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent or other industrial or intellectual property rights.

10/2016
www.philips.com